



Analysis of SiW-ECAL technological prototype beam test with electron beam



Y. Kato^B, K. Goto^A, T. Suehara^A
and ILD SiW-ECAL group
Kyushu University^A
The University of Tokyo^B



LCWS2019 @ Sendai, Japan
29th Oct. 2019


Table of Contents

- R&D of SiW-ECAL technological prototype
 - FEV13-Jp Status
- Beam Test 2019
- Procedure for Energy Measurement
- Analysis
 - Trigger adjustment
 - Masked channels
 - Pedestal uniformity / stability
 - MIP calibration
 - Shower
- Remaining Issues


R&D of SiW-ECAL technological prototypes

Major changes in FEV11 → 13 and SMBv4 → v5


- ASIC: SKIROC2 → 2A
 - Individual threshold control
 - Improvements on TDC
- Smaller SMB footprint
- Connection by 0.4mm-pitch flex cables
 - Two candidates, footprint compatible



FEV11 & SMBv4




FEV13 & SMBv5



Analogue core: SKIROC2A

- Outputs: Gain (High/Low), TDC



arXiv:1801.02024

FEV1 3-Jp Status

- ASIC: SKIROC2A
- Si thickness: 320 μ m & 650 μ m **New!**
 - 256 ch/sensor \times 4 sensor/slab
- FEV-SMB Connection: Flexible cable or Micro-coaxial cable
- EM shielding: w/ Carbon frame and cover
- Power Pulsing

➤ See previous talk for details




Total 5 slabs
in Kyushu U., Japan

slab ID	P1	P2	P3	K1	K2
Si thickness	650 μ m	650 μ m	320 μ m	650 μ m	650 μ m
Assembly	in Kyushu U.	in Kyushu U.	in Kyushu U.	in LLR	in Kyushu U.

Beam Test 2019 @ DESY

- Beam time:
 - 24th June - 7th July at DESY test beam facility
 - e⁻ beam: 1 - 5 GeV
- Presence from:
- Support & Hardware from:





Beam Test 2019 @ DESY

- Beam time:
 - 24th June - 7th July at DESY test beam facility
 - e⁻ beam: 1 - 5 GeV
- Objectives:
 - Comparison of ASU based on BGA and based on Chip-On-Board (COB)
 - Test of new SL-Boards (SLB)
 - Validation of FEV13-Jp ← Target of this talk
- Programs:

<u>MIP program (w/o Tungsten)</u> <ul style="list-style-type: none">◦ <u>Position scan for MIP calibration</u>◦ TDC test◦ Angled beam: 25 deg.◦ <u>Retriggering / double pedestal</u>	<u>Shower program (w/ Tungsten)</u> <ul style="list-style-type: none">◦ <u>Energy measurement</u>◦ Response from large signal◦ TDC / auto gain◦ Edge effect
--	--

Setup for Beam Test

- Devices: 2 types of readouts
 - DIF based slabs: FEV13-Jp × 5
 - SLB based slabs:
 - COB × 2
 - FEV12 × 2
- Absorber: Tungsten
 - $X_0 = 3.5$ mm, $R_M = 9$ mm, $\lambda_0 = 96$ mm



Procedure for Energy Measurement

Single Slab Analysis

1. Trigger adjustment & Masking of noisy channels
2. Pedestal calibration
16 chips × 64 channels × 15 memories
3. Gain calibration using MIP
16 chips × 64 channels

Multi Slab Analysis [in progress]

1. Timing coincidence
using bunch crossing ID (BCID): $\Delta t = 0.2 \mu\text{s}$
2. Event Building

Trigger Adjustment

- Threshold scan is performed for estimation of S/N_{Trig} and trigger adjustment.

$$S/N_{Trig} \equiv \frac{\mu_{2MIP} - \mu_{1MIP}}{\sigma_{1MIP}}$$



- Test pulse of {4.2, 8.4} fC is injected.
 - 4.2 fC: 1 MIP for 320 μ m
- S-curve is fitted by Err-function.

$$f(x) = A \times \text{Erfc}\left(\frac{x - \mu}{\sqrt{2}\sigma}\right) + \text{const.}$$


Injection [fC]	4.2	8.4
mean [DAC]	265.4	340.4
sigma [DAC]	12.0	12.5
S/N_{Trig}	6.4 \pm 0.8	

- Trigger is set as 0.5 MIP of 320 μ m slab: \sim 230 DAC.

S/N_{Trig} is worse (previous: 11.6), under investigation.



P1, all chips, ch 58-63






Masking of Noisy channels

- A few channels are noisy after trigger adjustment and masked: 1 - 2 %.
- Individual threshold control was not used because it wasn't ready. → Next TB

slab P1



slab P2

slab P3




slab K1

slab K2




Pedestal Analysis

- Non-triggered ADC output (around ~300 [ADC])
- Fitted by Gaussian



Pedestal Uniformity: Mean

- Mean of Gaussian
- Result of 1st Memory (Memory-cell dependence is referred later.)




➤ Although there are differences between chips, mean of pedestals looks generally uniform within the same chip.

Pedestal Uniformity: Width

- Sigma of Gaussian
- Result of 1st Memory (Memory-cell dependence is referred later.)


P3-chip0 looks strange.
This chip may be broken.



➤ Width of pedestal is almost uniform (3~4) throughout.

Pedestal Stability


- Pedestal stability is confirmed in this beam time.



MIP event

- MIP program is performed for mainly energy calibration of all the pixels.
- Hit map: Sum of the triggered events
- Event display: ADC output of single event after event building


➤ Electron energy: 3 GeV



MIP spectrum

- Typical MIP spectrums of each slabs are shown.
- Pedestal is subtracted.
- Fitted by Lan-Gaus function.
 - Convolution of Landau × Gaussian
- MPV: Most Probable Value
- Definition of S/N_{ADC} :


$$S/N_{ADC} \equiv \frac{MPV_{1MIP}}{Width_{pedestal}}$$



slab	P1	P2	P3	K1	K2
thickness	650μm	650μm	320μm	650μm	650μm
MPV	146.5	144.9	71.3	141.4	146.1
Ped_width	3.0	3.0	3.3	2.8	3.1
S/N	49.0	48.9	21.7	50.2	47.5


MIP calibration

- MPV maps:





MIP calibration

- slab: P1






Chip0 is broken?



Preliminary

MIP calibration

- slab: P2




Preliminary



Low-statistics because
DIF was broken in position scan

MIP calibration

- slab: P3




Chip0 is broken?



Preliminary



MIP calibration

- slab: K1



HV connection is bad?




entries



Preliminary

MIP calibration

- slab: K2




Good!

Preliminary

MIP calibration: Summary


- MPV maps:



Shower event


- Using the preceding results, we can finally build events.
 - BCID offsets between SLB-based and DIF-based are corrected.
- A typical event is checked with event display.
 - In this picture, color scale is not converted to energy, still ADC output.

Event display of shower event



Shower Analysis: Hit Energy

- Hit energy after MIP calibration (run_42003)
Single cell hit energy in 3 GeV e^- beam






Simulation

- We performed detector simulation for this beam test.
- Simulator: DDSim in iLCSoft



- Structure of FEV13-Jp:

- CF: 0.6mm
- Electronics(Air)
- PCB: K1: 1.6mm, others: 1.8mm
- Glue(Air): 0.08mm
- Si: 0.32mm or 0.65mm
- Glue(Air): 0.08mm
- Kapton(Cu): 0.06mm
- CF: 0.6mm
- Plastic(polyethylene): 5mm




Comparison of Measured and Simulated.

- Simulated results are converted to MIP units and compared to measured ones.
- Work in progress.



TDC Correlation with MIP




- Correlation of TDC between slab P1 and P2
- Select 1 ch (at the center of the beam), $450 < \text{ADC} < 500$ (to avoid time-walk)
- $\sim 10 / 1$ ns at the normal slope: timing resolution \sim a few ns?
- TDC calibration in progress.

Correction of Time Walk




Very Preliminary

- Time Walk: TDC dependence on ADC
- TDC-interval vs ADC are fitted by Log function.
- Width of TDC-interval is improved: 117 → 52.


TDC interval



ADC



before



after

from previous talk,


- TDC to real time calibration factors
- 0.127 ns / TDC count (up)
- 0.066 ns / TDC count (down)

timing resolution:
5.2 ± 1.6 ns


Remaining Issues

Double pedestal / Retrigger

- run 32015, slab P1





Retrigger event:
BCID is consecutive.



Double pedestal
by retrigger

Pedestal difference between ADC/TDC mode


- We found the difference of pedestals between ADC/TDC mode.
- Memory-cell dependence is not same.
- In the first memory cell, the difference of typical Ped_mean is ~ 15 .




Pedestal difference between ADC/TDC mode

- We found the difference of pedestals between ADC/TDC mode.
- Memory-cell dependence is not same.
- In TDC mode, SCA~2 is worse.

run 32004-010, ASIC 12 (beam)





run 32015, ASIC 13 (beam)



Pedestal difference between ADC/TDC mode

- We found the difference of pedestals between ADC/TDC mode.
- Memory-cell dependence is not same.
- In TDC mode, SCA~2 is worse.



- There are double pedestal even after bcid selection in TDC mode.
- The criteria for identification of double pedestal is not optimized.

Work in progress.

Summary

- FEV13-Jp: 5 slabs from Kyushu U.
- BT 2019 DESY: All the slabs worked consistently.
- Pedestal study
 - Uniformity and Stability is verified.

- MIP calibration
 - MIP calibration is almost completed.
 - S/N is obtained for 5 slabs:

slab	P1	P2	P3	K1	K2
thickness	650 μ m	650 μ m	320 μ m	650 μ m	650 μ m
S/N _{ADC}	49.0	48.9	21.7	50.2	47.5

- Shower analysis
 - Event building has done and shower event is seen in event display.
 - We take a look at hit energy which is consistent with simulation result.
 - Work in progress.
- TDC test
 - Time walk is corrected, but very preliminary.
 - Timing resolution is obtained, however we need more detail study using injection.
- Several issues remain:
 - Retriggered events are removed practically although the cause is still unknown.
 - In TDC mode, pedestals become worse because of retriggers.

backup


R&D of SiW-ECAL technological prototypes



ASU: 12 years of R&D

Most complex element: electro-mechanical integration

- Distrib / Collect signals from VFE (ASICs), Analog & Digital with dyn. range ≥ 7500
- Mechanical placer & holder for Wafers \rightarrow precision
- Thickness constraints



Milestone	Date	Object	Details	REM
1 st ASIC proto	2007	SK1 on FEV4	36 ch, 5 SCA	proto, lim @ 2000 mips
1 st ASIC	2009	SK2	64ch, 15 SCA	3000 mips
1 st prototype of a PCB	2010	FEV7	8 SK2	COB
1 st working PCB	2011	FEV8	16 SK2 (1024 ch)	CIP (QGFP)
1 st working ASU in BT	2012	FEV8	4 SK2 readout (256ch)	best S/N ~ 14 (HG), no PP retriggers 50-75%
1 st run in PP	2013	FEV8-CIP		BGA, PP
1 st full ASU	2015	FEV10	4 units on test board 1024 channel	S/N ~ 17-18 (High Gain) retrigger ~ 50%
1 st SLABs	2016	FEV11	7 units	
pre-calo	2017	FEV 11	7 units	S/N ~ 20 (12) _{Trig.} 6-8 % masked
1 st technological ECAL	2018	SLABvFEV11 & FEV13 SK2a+ Compact stack	SK2 & SK2a (>timing)	Improved S/N Timing...

Vincent.Boudry@in2p3.fr

SiW-ECAL introduction | CALICE meeting

R&D of SiW-ECAL technological prototypes

Beam-test 2015-2018

CERN 2015

"Naked FEV11"

2 hours muon runs, all pedestals with > 1000 hits

Hybrids per pedestal (2 hours)

Stats: $\mu = 1.2$, $\sigma = 0.5$, $\text{skew} = 0.1$, $\text{kurt} = 0.1$

Defaults cataract:

- Negative signals
- re-triggers
- ~ high thr.
- sq events / 10

DESY 2018

7 FEV11 + 1 FEV13(650 μ m)

DESY 2018

7 FEV11 + 1 FEV13(650 μ m)

$S/N_{ADC} = 16-17$
(MIP - ped) / σ_{ped}

Defaults cataract:

- Negative signals
- re-triggers
- ~ high thr.
- sq events / 10

Threshold [DAC]

1 MIP

$\sqrt{2}$ MIP

Slab 17, 18, 19, 20

$S/N = 11.6 \pm 0.7$

DESY 2018

7 FEV11 + 1 FEV13(650 μ m)

$S/N_{Trig} \sim 11.6 \pm 0.7$

Trigger \rightarrow ~1/3 mip (est.)

First comm. of FEV13

nit_mip

Statistics: Entries: 10214, Mean x: -29.515, Mean y: 9.124, Std Dev x: 49.013, Std Dev y: 47.5236

DESY 2017

7 FEV11

Single cell energy distribution for 3 GeV μ beam irradiation

Energy [GeV]

Statistics: Entries: 10000, Mean: 1.000, Std Dev: 0.000, Min: 0.999, Max: 1.001

S-N in the charge measurement (all layers)

Statistics: Entries: 1000, Mean: 2000, Std Dev: 1500, Min: 1000, Max: 3000

$S/N_{ADC} = 20.3$

$\sigma_{S/N} = 1.5$ (7.4 %)

masked ch. ~ 8 %

Hit eff. ~ 99.95 %

0°, 45° ✓

1T operation ✓

CERN 2018

6 FEV11 + 1(4) FEV13(320 & 650 μ m) + 24X₀ W

SDHCAL

SIW-ECAL

Layer #6, pedestal position (ADC) map for SCA = 0

ADC

CERN 2018

6 FEV11 + 1(4) FEV13(320 & 650 μ m) + 24X₀ W

Masked ch (FEV11) ~ 4 %

z_barycenter_vs_nhits

N_hits

e⁻

μ

z

Taikan

Vince | -ECAL introduction | CALICE meeting | Utrecht uni, 10/04/2019