ILC – GENERAL INSTALLATION EQUIPMENT

Presentation to LCWS Workshop in Beijing 27 March 2010

Outline

- General issues
- ILC cryo-modules
- Underground transport and handling solutions
- Conclusion
- □ (Slope facts and issues)

Need to consider all phases

- Delivery of components
- Assembly
- Test
- Storage (LHC experience –this will be needed)
- Transfer to shaft (road transport)
- Lowering (crane or lift ?)
- Loading underground
- Transport along tunnel (co activities)
- Unloading / Transfer onto supports (time constraints)
- **Removal for repair**

Integration issues

Space for transport , unloading and transfer

- With guidance error margin
- Allow co-activity (passage next to transport zone)
- Space for power rail
- Space for loading lowered items
- Consider logistics (parking and passing places)
- Integration should include space for removal
- Try to integrate transport and handling design issues into equipment and infrastructure design at an early stage.

CIVIL ENGINEERING TOLERANCES

- Important to know how much space is available for transport.
- LHC experience LEP tunnel moves with respect. to beam line – this can make up to 100mm difference to space available at junction floor to tunnel wall
- Assumption after discussion with J Osborne: Space available will be as shown on theoretical drawings (CE tolerances will be specified accordingly)
- > Tunnel floor is always much more stable and more exact than tunnel ceiling. Preferable to install heavy machine components on the floor.

SLOPES...

Effect of slope on vehicle design:
Need more traction force
Need more braking force
Cooling of motors (duty factor)
Cooling of brakes
Bigger vehicle (integration)

ILC - Transport Study Specification Sheet

FNAL, Dec. 10, 2008

ILC Cryomodules

Equipment Description	Vinit	Unit	Source of Information/Comments
Length	12.65	Meters	This is the length given in the ILC RDR of a future ILC-
			DESY TTE, XEEL, and Fermilab NML Test Facility is 11.98
	1 1		meters. The length of the "Type 4" design developed at
			Fermilab is 12.35 meters (See "Cryomodule Dimensions"
117 446		Hataa	drawing).
width	1.67	Meters	A crymodule, including the survey arm and attached
			coupler motor (See "Cryomodule Dimensions" drawing).
			At one time, there was some discussion of moving the
			survey arm to the other side of the cryomodule to reduce
Height	1.34	Meters	This is th total transport height of the Type 3+ and Type
			4 cryomodule, without any support feet or transportation
			device (See "Cryomodule Dimensions" drawing).
Walaba	1000	Davada	Asian second weight of the Taxa Dataset data with
weight	16260	Pounds	Actual measured weight of the Type 3+ cryomodule with interconnect belows attached. An ILC-type cryomodule
			will be slightly heavier due to exta 0.67 meter length.
Support Points	8.30 x 0.64	Meters	This the distance between the support points on the
	1		bottom of the Type 3+ cryomodule (along the beamline, and transverse to the beamline, respectively). See
	1		"Cryomodule Attachment Points" drawing for details. The
1			details of the support stand currently used at DESY and
1			Fermilab are shown on the "Adjustable Support
	1		Assembly" drawing. A new support stand will most likely
Ifting Points	6 80 × 0.64	Mataur	be designed for the ILC. This the distance between the attachment exists for the
Litting Politis	0.00 x 0.64	Pieters	lifting fixture on the top of the Type 3+ cryomodule
			(along the beamline, and transverse to the beamline,
	1		respectively). See "Cryomodule Attachment Points"
			drawing for details.
Lifting Fixture Weight	4940	Pounds	The lifting focure is used to lift the Type 3+ cryomodule with an ouerband crane. It has a load capacity of 10-
	1		tons (20,000 pounds).
Transportation Fixture	2840	Pounds	The transportation fixture was designed at Fermilab by
	1		Mike McGee to minimize vibration of the cryomodule
	1		while transporting it on a truck. Details of this system
			nave been well documented and tested and can be provided. If needed.
Maximum Acceleration	1.5	G	The conservative maximum value of acceleration for the
			Type 3+ cryomodule in the vertical, transverse, and
	1		longitudinal direction. This value was provided by Mike
	1		Research Neell, who was contracted by DEEY to study
	1		this. It has been determined through actual transport
	1		studies that somewhat higher accelerations are safe.
	1 1		More detailed information can be provided, if needed.
Natural Fragmancies	0.11	He /v u and a)	These fractionalist are require of actual measurements
Natural Prequencies	3-11	Hz (x, y, and z)	during transport studies. There are also calculated
	1		frequencies from Finite Element Analysis (FEA) modeling
	1		that agree very well with these measurements. Details
	I 1		
			can be provided, if needed. (x is transverse, y is vertical,
			can be provided, if needed. (x is transverse, y is vertical, and z is longitudinal)
	13-15	Hz (x and z) Hz (x, y, and z)	can be provided, if needed. (x is transverse, y is vertical, and z is longitudinal)
	13-15 19 21-23	Hz (x and z) Hz (x, y, and z) Hz (x, y, and z)	can be provided, if needed. (x is transverse, y is vertical, and z is longitudinal)
Quantity to be Transported & Installed	13-15 19 21-23 1680	Hz (x and z) Hz (x, y, and z) Hz (x, v, and z) Cryomodules	can be provided, if needed. (x is transverse, y is vertical, and z is longitudinal) This it the quantity of cryomodules given in the ILC RDR.
Quantity to be Transported & Installed	13-15 19 21-23 1680	Hz (x and z) Hz (x, y, and z) Hz (x, v, and z) Cryomodules	can be provided, if needed. (x is transverse, y is vertical, and z is longitudinal) This it the quantity of cryomodules given in the ILC RDR for the Main Linac.
Quantity to be Transported & Installed Cryomodule String	13-15 19 21-23 1680	Hz (x and z) Hz (x, y, and z) Hz (x, v, and z) Cryomodules	can be provided, if needed. (x is transverse, y is vertical, and z is longitudinal) This it the quantity of cryomodules given in the ILC RDR. for the Main Linac. The ILC is broken up into a number of cryogenic strings. Each schime bac crowed "content and back and its.
Quantity to be Transported & Installed Cryomodule String	13-15 19 21-23 1680	Hz (x and z) Hz (x, y, and z) Hz (x, v, and z) Cryomodules	can be provided, if needed. (x is transverse, y is vertical, and z is longitudinal) This it the quantity of cryomodules given in the ILC RDR. for the Main Linac. The ILC is proken up into a number of cryoperic strings. Each string has support "girdes" at each end to counteract the cryopenic vacuum leads, with a string of
Quantity to be Transported & Installed Cryomodule String	13-15 19 21-23 1680	Hz (x and z) Hz (x, y, and z) Hz (x, v, and z) Cryomodules	can be provided, if needed. (x is transverse, y is vertical, and z is longitudinal) This it the quantity of cryomodules given in the ILC RDR for the Main Linac. The ILC is broken up into a number of cryogenic strings. Each string has support "girdens" at each end to counteract the cryogenic vacuum koads, with a string of cryomodules in between. At this time, it is unclear as to
Quantity to be Transported & Installed Cryomodule String	13-15 19 21-23 1680	Hz (x and z) Hz (x, y, and z) Hz (x, v, and z) Cryomodules	can be provided, if needed. (x is transverse, y is vertical, and z is longitudinal) This it the quantity of cryomodules given in the ILC RDR for the Main Linac. The ILC is broken up into a number of cryogenic strings. Each string has support "girlders" at each end to counteract the cryogenic vacuum loads, with a string of cryomodules in between. At this time, it is unclear as to how long each of these strings will be. The "Cryomodule
Quantity to be Transported & Installed Cryomodule String	13-15 19 21-23 1680	Hz (x and z) Hz (x, y, and z) Hz (x, y, and z) Cryomodules	can be provided, if needed. (x is transverse, y is vertical, and z is longitudinal) This it the quantity of cryomodules given in the ILC RDR for the Main Linac. The ILC is broken up into a number of cryopenic strings. Each string has support "girders" at each end to counteract the cryopenic vecuum leads, with a string of cryomodules in between. At this time, it is unclear as to how long each of these strings will be. The "Cryomodule Attachment Points" drawing shows a schematic of a
Quantity to be Transported & Installed Cryomodule String	13-15 19 21-23 1680	Hz (x and z) Hz (x, y, and z) Hz (x, y, and z) Cryomodules	can be provided, if needed. (x is transverse, y is vertical, and z is longitudinal) This it the quantity of cryomodules given in the ILC RDR for the Main Linac. The ILC is broken up into a number of cryogenic strings. Each string has support "girdens" at each end to counteract the cryogenic vacuum koads, with a string of cryomodules in between. At this time, it is unclear as to how long each of these strings will be. The "Cryomodule Attachment Points" drawing shows a schematic of a cryogenic string.
Quantity to be Transported & Installed Cryomodule String Interconnection Details	13-15 19 21-23 1680	Hz (x and z) Hz (x, y, and z) Hz (x, v, and z) Cryomodules	can be provided, if needed. (x is transverse, y is vertical, and z is longitudinal) This it the quantity of cryomodules given in the ILC RDR for the Main Linac. The ILC is broken up into a number of cryogenic strings. Each string has support "girles" at each end to counteract the cryogenic vacuum loads, with a string of cryomodules in between. At this time, it is unclear as to how long each of these strings will be. The "Cryomodule Attachment Points" drawing shows a schematic of a cryogenic string. The interconnects between each cryomodule within a cryoeneric string.
Quantity to be Transported & Installed Cryomodule String Interconnection Details	13-15 19 21-23 1680	Hz (x and z) Hz (x, y, and z) Hz (x, v, and z) Cryomodules	can be provided, if needed. (x is transverse, y is vertical, and z is longitudinal) This it the quantity of cryomodules given in the ILC RDR for the Main Linac. The ILC is broken up into a number of cryogenic strings. Each string has support "ginders" at each end to counteract the cryogenic vacuum loads, with a string of cryomodules in between. At this time, it is unclear as to how long each of these strings will be. The "Cryomodule Attachment Points" drawing shows a schematic of a cryogenic string. The interconnects between each cryomodule within a cryogenic string consist of several cryogenic pipes, a vacuum beamline, and a large interconnect belows. At
Quantity to be Transported & Installed Cryomodule String Interconnection Details	13-15 19 21-23 1680	Hz (x and z) Hz (x, y, and z) Hz (x, y, and z) Cryomodules	can be provided, if needed. (x is transverse, y is vertical, and z is longitudinal) This it the quantity of cryomodules given in the ILC RDR for the Main Linac. The ILC is broken up into a number of cryogenic strings. Each string has support "girlders" at each end to counteract the cryogenic vacuum loads, with a string of cryomodules in between. At this time, it is unclear as to how long each of these strings will be. The "Cryomodule Attachment Points" drawing shows a schematic of a cryogenic string. The interconnects between each cryomodule within a cryogenic string consist of several cryogenic pipes, a vacuum beamline, and a large interconnect belows. At the ends of each cryogenic string is a cryogenic string.
Quantity to be Transported & Installed Cryomodule String Interconnection Details	13-15 19 21-23 1680	Hz (x and z) Hz (x, y, and z) Hz (x, y, and z) Cryomodules	can be provided, if needed. (x is transverse, y is vertical, and z is longitudinal) This it the quantity of cryomodules given in the ILC RDR. for the Main Linac. The ILC is broken up into a number of cryogenic strings. Each string has support "girdes" at each end to counteract the cryogenic vacuum leads, with a string of cryomodules in between. At this time, it is unclear as to how long each of these strings will be. The "Cryomodule Attachment Points" drawing shows a schematic of a cryogenic string. The interconnects between each cryomodule within a cryogenic string area in section. The details of these
Quantity to be Transported & Installed Cryomodule String Interconnection Details	13-15 19 21-23 1680	Hz (x and z) Hz (x, y, and z) Hz (x, v, and z) Cryomodules	can be provided, if needed. (x is transverse, y is vertical, and z is longitudinal) This it the quantity of cryomodules given in the ILC RDR for the Main Linac. The ILC is broken up into a number of cryogenic strings. Each string has support "girders" at each end to counteract the cryogenic vacuum loads, with a string of cryomodules in between. At this time, if is unclear as to how long each of these strings will be. The "Cryomodule Attachment Points" drawing shows a schematic of a cryogenic string. The interconnects between each cryomodule within a cryogenic string orosist of several cryogenic pipes, a vacuum beamline, and a large interconnect belows. At the ends of each cryogenic string is a cryogenic end/feed cap and a warm vacuum section. The details of these interconnects are very complicated and require detailed
Quantity to be Transported & Installed Cryomodule String Interconnection Details	13-15 19 21-23 1680	Hz (x and z) Hz (x, y, and z) Hz (x, y, and z) Cryomodules	can be provided, if needed. (x is transverse, y is vertical, and z is longitudinal) This it the quantity of cryomodules given in the ILC RDR for the Main Linac. The ILC is broken up into a number of cryogenic strings. Each string has support "girles" at each end to counteract the cryogenic vacuum loads, with a string of cryomodules in between. At this time, it is unclear as to how long each of these strings will be. The "Cryomodule Attachment Points" drawing shows a schematic of a cryogenic string. The interconnects between each cryomodule within a cryogenic string. The interconnects are very complicated and require detailed discussions.
Quantity to be Transported & Installed Cryomodule String Interconnection Details Tunnel Size	13-15 19 21-23 1680 4.5	Hz (x and z) Hz (x, y, and z) Hz (x, v, and z) Cryomodules Meters	can be provided, if needed. (x is transverse, y is vertical, and z is longitudinal) This it the quantity of cryomodules given in the ILC RDR for the Main Linac. The ILC is broken up into a number of cryogenic strings. Each string has support "girlers" at each end to counteract the cryogenic vecuum leads, with a string of cryomodules in between. At this time, it is unclear as to how long each of these strings will be. The 'Cryomodule Attachment Points' drawing shows a schematic of a cryogenic string. The Interconnects between each cryomodule within a cryogenic string is a gregoric string is a cryogenic end/feed tap and a warm vacuum section. The details of these interconnects are very complicated and require detailed discussions.
Quantity to be Transported & Installed Cryomodule String Interconnection Details Tunnel Size	13-15 19 21-23 1680 4.5	Hz (x and z) Hz (x, y, and z) Hz (x, y, and z) Cryomodules Meters	can be provided, if needed. (x is transverse, y is vertical, and z is longitudinal) This it the quantity of cryomodules given in the ILC RDR for the Main Linac. The ILC is broken up into a number of cryogenic strings. Each string has support "girlders" at each end to counteract the cryogenic vacuum loads, with a string of cryomodules in between. At this time, it is unclear as to how long each of these strings will be. The "Cryomodule Attachment Points" drawing shows a schematic of a cryogenic string. The interconnects between each cryomodule within a cryogenic string. and a large interconnect belows. At the ends of each cryogenic string is a cryogenic spipes, a vacuum beamline, and a large interconnect belows. At the ends of each cryogenic string is a cryogenic data interconnects are very complicated and require datailed discussions. This is the inner diameter of the Main Unac Beam tunnel given in the ILC RDR. See "4.5M Service and Beam Tunnel Plan B Elev." drawing.
Quantity to be Transported & Installed Cryomodule String Interconnection Details Tunnel Size Position in Tunnel Cross-Section	13-15 19 21-23 1660 4.5	Hz (x and z) Hz (x, y, and z) Hz (x, v, and z) Cryomodules Meters	can be provided, if needed. (x is transverse, y is vertical, and z is longitudinal) This it the quantity of cryomodules given in the ILC RDR for the Main Linac. The ILC is broken up into a number of cryogenic strings. Each string has support "girdes" at each end to counteract the cryogenic vacuum loads, with a string of cryomodules in between. At this time, it is unclear as to how long each of these strings will be. The "Cryomodule Attachment Points" drawing shows a schematic of a cryogenic string. The interconnects between each cryomodule within a cryogenic string. The interconnects between each cryomodule within a cryogenic string. The interconnects between each cryomodule within a cryogenic string. The interconnects are very complicated and require detailed discussions. This is the inner diameter of the Main Linac Beam tunnel given in the ILC RDR. See "4.5M Service and Beam Tunnel Plan & Elev."
Quantity to be Transported & Installed Cryomodule String Interconnection Details Tunnel Size Position in Tunnel Cross-Section	13-15 19 21-23 1660 4.5	Hz (x and z) Hz (x, y, and z) Hz (x, y, and z) Cryomodules Meters	can be provided, if needed. (x is transverse, y is vertical, and z is longitudinal) This it the quantity of cryomodules given in the ILC RDR for the Main Linac. The ILC is broken up into a number of cryogenic strings. Each string has support "ginders" at each end to counteract the cryogenic vacuum loads, with a string of cryomodules in between. At this time, it is unclear as to how long each of these strings will be. The "Cryomodule Attachment Points" drawing shows a schematic of a cryogenic string. The interconnects between each cryomodule within a cryogenic string are large interconnect belows. At the ends of each cryogenic string is a cryogenic end/feed locasition. This is the inner diameter of the Main Linac Beam tunnel given in the ILC RDR. See "4.5M Service and Beam Tunnel Plan & Etv." drawing. See "4.5M Service and Beam Tunnel Plan & Etev." drawing.



Picture of the first cryo-module on its green support girders at Fermilab (cryogenic components not installed). Response from Jerry Leibfritz, FNAL

- This is what is used at DESY for FLASH and CMTS, and also at the Fermilab ILCTA.
- It is based on the large support girder that sits underneath the first and last cryo-modules of a string to counteract the large vacuum load and prevent movement of the cryo-module. The support stand sits on top of this girder.
- The cryogenic feedbox and endcaps are designed for this elevation and it would have been too expensive for us at Fermilab to redesign this, so we used basically the same design as DESY.
- When we were initially laying out the ILC tunnel, we tried to maximize the use of space, so we set the elevation of the cryo-module to be in the widest part of the diameter of the tunnel, allowing us to move it as close to the wall as possible.
- For a machine as big as the ILC, these components could be redesigned, so the cryo-module sits lower, but it would require some engineering effort.
- THE CURRENT BEAM POSITION IS HIGH ENOUGH TO ALLOW THE USE OF TRANSPORT VEHICLES WHICH INCLUDE THEIR OWN TRANSFER CAPABILITY; IT IS THEREFORE INTERESTING TO LEAVE IT WHERE IT IS!

Further discussions with Jerry Leibfritz

- 860mm (700 mm?) clearance underneath confirmed
- Interconnect clearance about a couple of cm.
- Lateral transfer OK (vertical OK for interconnects)
- Support anywhere (except bellows retraction space)
- Space under cryo-module can be left clear (cabling etc can be on floor on wall side of cryo-module)
- Assume a waveguide crossing tunnel at each cryomodule (headroom during operation).

LHC installation

LHC	n°	Length (incl. protection covers)	Dimension	Weight	
Cryo-dipoles	1232 (+16)	16.4 m	Ø 1.1 m	34 t	42′ 432
Cryo- quadropoles	360 arc 64 DS 90 LSS	7.5 m 9 – 10.5 m 7.5 – 15 m	Ø 1.1 m	8.5 t 5 – 23 t 5 – 23t	3'060 760 1'373
Resistive	205	1.2 - 6.4 m	max width 1.1m max height 1.1m	3 – 18t	1′025 (est.)
Total					48'650 t

Difficulties for LHC cryodipole tunnel transport / installation

Space

- Laterally during transport and unloading
- Underneath when placing on supports
- Transport and installation blocks tunnel
- Overlapping interconnects (horizontal transfer)
- Fragility (cold feet)
- Proximity of support and lifting points
- Precise positioning needed to put on jacks
- One lowering shaft for whole ring

Implications

- Separate transport, unloading and transfer equipment
- Complex (prototype) very compact equipment
- Shock-log monitoring of each magnet
- Approx 2 hours to unload
- Complicated logistics







LHC Cryodipole installation sequence









Lift magnet



Trailer height 530 mm resp. 500 mm













■ Lifting stroke 250 mm









Roll unloading equipment under magnet

















Lift magnet


Withdraw trailer







Lower magnet











Install transfer tables





Withdraw unloading equipment



Measure positions



Transfer onto supports









Re-connect convoy



Go to get the next one



LHC trailer and transfer tables

Advantages

- Allows installation with very limited clearance (250 to 300 mm) underneath the cryo-module
- Transfer tables allow small longitudinal corrections during resp. after lateral movement
- Disadvantages
 - Very sophisticated, complex and consequently maintenance intensive
 - Tunnel almost entirely blocked during transport operation
 - Collisions possible despite optical guiding system, anti collision system, low speed of max 3 km/h and two operators -> For safety reasons transports >250 kg are not allowed next to 'cold' LHC machine! Installation of solid barriers all along the LHC would be required.

LHC Buggies can move at 180 deg to transport direction





Capacity: Equipment height: 9 t per buggy 560 mm



















LHC buggies

Advantages

- All-in-one solution for longitudinal transport and lateral transfer
- No longitudinal offset when wheels turn 180°
- Can operate within a limited time on slopes up to 7%
- Operator friendly
- Disadvantages
 - Require considerable clearance (>500 mm) underneath the cryomodule
 - Require very exact positioning since the jacks can only compensate for a very slight misalignment
 - Tunnel almost entirely blocked during transport operation
 - Collisions possible despite optical guiding system, anti collision system, low speed of max 3 km/h and two operators -> For safety reasons transports >250 kg are not allowed next to 'cold' LHC machine! Installation of solid barriers all along the LHC would be required.

LEP monorail system



Suspended monorail train

Advantages

- Fixed mechanical guiding system
- Not depending on floor conditions
- No or very limited risk of collisions with installed machine components during transport operation -> big advantage when machine is 'cold'
- Rail also used for fixation of power feed rail
- Tunnel not entirely blocked during transport operation
- Remote controlled operation easily feasible
- Could be configured to operate on slopes
- Can transport several cryo-modules at once
- Can transport all kind of equipment
- Disadvantages
 - Integration issue may conflict with waveguides or other overhead installations?
 - Lateral transfer solution to be assessed i.e. transfer table.

SPS TRAILER CRANE UNIT
































SPS trailer / crane unit

Advantages

- All-in-one solution for longitudinal transport and lateral transfer
- Operator friendly
- Requires clearance only for the outriggers
- Disadvantages
 - Require very exact positioning since the jacks can only compensate for a very slight misalignment
 - Tunnel almost entirely blocked during transport operation
 - Collisions possible no optical guiding system, no anti collision system but more space than in LHC

DESY - Trailer transfer table unit







Equipment height 1m

DESY trailer / transfer table unit

Advantages

- All-in-one solution for longitudinal transport and lateral transfer
- Operator friendly
- Requires clearance only for the outriggers
- Disadvantages
 - Require very exact positioning since the jacks can only compensate for a very slight misalignment
 - Collisions possible no optical guiding system, no anti collision system but more space than in LHC



Capacity: Lifting height:

6 t per lifting platform 2.4 m



DESY trailer / lifting table unit

Advantages

- All-in-one solution for longitudinal transport and lateral transfer
- No or very limited risk of collisions with installed machine components during transport operation -> big advantage when machine is 'cold'

Disadvantages

- Require very exact positioning since the ceiling support frames can only compensate for a very slight misalignment
- More difficult to install overhead
- Civil Engineering tolerances more problematic
- Longitudinal forces, vibrations, oscillations etc.?
- LHC incident scenario?
- Handling/storage rule: Light staff up, heavy stuff down

Discussion – Buggies

- The 700 mm clearance below cryo-modules allows the use of a combined transport and transfer vehicle such as the LHC buggies.
- The LHC buggies were designed for slope of 8% but did overheat after intensive use on slopes
- The transfer using buggies is carried out by rotating the wheels through 90 degrees. The space between ends of LHC warm magnets when being installed is approx 7cm – longitudinal alignment relied on the operators' skill and care.
- The space between the ends of ILC cryo-modules is approx 2cm – this would lead to risk of damage using buggy –type solution relying on operator skill for large numbers (1600) modules unless some automated alignment is provided.
- The LHC buggies were used for transporting warm magnets – less delicate than cryo-modules.

CONCLUSION

- All presented underground transport and handling solutions offer some advantages but also disadvantages.
- Considering the dimensions and characteristics of the cryomodule an 'All-In-One' type equipment seems to be the most adapted.
- The LHC buggies are 560mm high: for ILC the 860mm clearance underneath cryo-modules will allow incorporation of cradles, load suspension, additional cooling and precise positioning tables to allow accurate longitudinal (and vertical?) alignment during lateral transfer onto jacks.
- A suspended monorail train system offers the safest and fastest transport solution but may create important integration problems.

NOTES ON SLOPES

Standard electric vehicles

Typically 1.5-2% slope for continuous use at full rated load with increased slope the load capacity or the use factor reduces. (see performance chart)

Encyclopedie de la Manutention

□ "rampe ≥ 7% = problème délicate" (this is with unbraked trailers)

 Effect of 2% slope is to double traction force needed compared with horizontal surface.



Specification "Eidechse" EFZ 302 AC

431,099,0001-A

	8	Layout plan for	indus	trial trucks	
		acc. to	VDI 21	98	
		Tra	ctors		
-	1.1	Manufacturer (Abbreviation)	TT	MAEL	
0	12	Type (Manufaturer's designation)	++	MAFI	
steristic	12	Dete	+	EFZ 302 AC	
	1.3	Drive		Electric	
arao	1.4	Operation		from driver's seat	
S	1.5	Load capacity	t		
	1.7	Nominal tractive force	N	4000	Pis.
s	1.9	Wheel base	mm	1365	Schalang A
ght	2.1	Dead weight (incl. battery)	kg	2500	
Wei	2.2	Axle load with load at front/at rear	kg	-	
-	2.3	Axle load without load at front/at rear	kg	1000 / 1500	
Sis	3.1	Tyres		Air	◎ ● □ □ □ □ □ □ □ □ □ □ □ □ □ □ □ □ □ □
has	3.2	Tyre size, front		6.00-9	
s, C	33	Tyre size, rear		6.00-9	
heels	3.5	Wheels numbers at front/rear (x = powered)		2/2x	420 1390 430 1060
N	3.6	Wheel track, at front	mm	888	550
	3.7	Wheel track, at rear	mm	888	2360 Cabin (option)
	4.7	Height with cabin	mm	2375	
	4.8	Seat height (SIP as per ISO 5353)	mm	1320	Permissible distance covered (m)
	4.12	Coupling height	mm	330	
suc	4.13	Platform level without load	mm	-	
USIC	4.16	Length of loading platform	mm	-	
c dime	4.17	Projecting length	mm	550	
	4.18	Width of loading platform	mm	-	
asi	4.19	Overall length	mm	2360	
"	4.21	Overall width	mm	1060	
	4.32	Road clearance (with nominal load)	mm	150	
ł	4.35	Turning radius	mm	2690	
	4.36	rotation	mm	1005	
	5.1	Driving speed with/without load	km/h	ca. 10 / 20	
ate	5.5	Traction force with/without load	N	- / 4400	
	5.6	Max. traction force with/without load	N	- / 15000	
tin	5.7	Gradability with/without load	%	-127	
1	5.8	Maximun gradability with/without load	%	- / 55	
	5.10	Service brake		hydraulic	
1	6.1	Drive motor, power output S2, 60 min	kW	15,6	
	6.3	Battery acc. to DIN 43536 A		5PzS	
	6.4	Battery voltage, nominal capacity	V/Ah	80/400L	
	6.5	Battery weight	kg	1049	
	6.6	Energy consumption	kWh/h	-	and an and a set of the set of th
0	8.1	Type of drive control		AC Inverter	
2	8.4	Sound level, driver's ear	dB (A)	-	
2 1		Trailer coupling kind/hoe DIN		three-stage	
	8.5	nanor oodpring, kinditype Dire		ando orago	

E:\Z\SPEZ_EID\431\099_0001_A_en[06.11.2003]



Example on effect of slope

In the example a tractor with a nominal towing capacity of 20 tonnes can be used on a 7% slope to tow a 6 tonne trailer a maximum of 3500m in one hour.

Other slope experience at CERN

Buggies for LHC warm magnet installation:

- Design for max slope 8%.
- During testing on 7% slope (several passes) overheated after approx 1hour.

Special purpose fork lift:

customized for 14% slope (needed continuous forced ventilation for brakes and motors)

Difficult to find supplier willing to do this.

Slope general comments

at this stage:

- 1.5 2% slope means can use standard vehicles (lowest cost most reliable solution)
- Up to 7 or 8% slope achievable by reducing standard vehicle capacity to approx one third of nominal (space issues?).
- Any steeper slopes will mean that it becomes more difficult to use standard equipment –this will have cost and reliability implications.
- In any case equipment for installing cryo-modules will be specially designed and built - but what about other equipment?

THANK YOU!

Any questions?

Acknowledgements

- Jerry Leibfritz / FNAL
- Norbert Meyners / DESY
- P. Brunero, Jan Francey, Jean-Louis Grenard, Keith Kershaw, ... / CERN

...